

PLEASE FIND A QUALIFIED ELECTRICIAN FOR INSTALLATION.

Please read the instruction before you install and use the luminaire.

LED GAS STATION CANOPY 60W/5700K/100-277V - SUPERIOR LIFE®

LED GAS STATION CANOPY 100W/5700K/100-277V - SUPERIOR LIFE®

SPECIFICATIONS

ITEM#	WATTS	COLOR	LUMENS	CRI	VOLT	DIMENSIONS
90001	60	5700K	5000	70	100-277V	15" x 15" x 2.4"
90003	100	5700K	8000	70	100-277V	15" x 15" x 2.4"

WARNING

Ensure power is off before starting installation, wiring or attempting any maintenance should be performed by a person familiar with the construction and operation of the product and hazards involved to ensure personal safety.

All work should be performed by a qualified electrician.


The mounting wall should be of sufficient strength; its endurance force must be greater than the fixture's weight.

The unit is designed for years with minimum care. For optimum performance, periodically clean the reflector and lens with a mild, non-abrasive glass cleaner and soft cloth. DO NOT use solvents or cleaners containing abrasive agents. When cleaning the fixture, make sure you have the power turned off and DO NOT spray liquid cleaner directly onto the LED, socket, or wiring.

INSTALLATION




Picture 1



Picture 2

4 Mounting screw holes (dia 0.24 in):

- Mounting Accessories (customer supplied):
- 4pcs M6 Hex head metal screws with nuts.
 - Junction Box
 - 1-8 UNC (2A) Stem




Picture 3

INSTALLATION 1

- 1: Cut a hole (minimum diameter 1.7 in) for stem into the canopy
- 2: To mount luminaire to canopy, insert and tighten 4pcs hex head self-drilling metal screws (minimum diameter 0.24 in). If the canopy is not strong enough for self-drilling screw, use 4 nuts to fix the screws from above the canopy. (picture 3)
- 3: Apply sealant around stem, hub and screw holes for a complete seal.

INSTALLATION 2



Picture 4

- 1: Cut a hole (minimum diameter 1.7 in) for stem into the canopy
- 2: To mount luminaire to canopy, insert and tighten 4pcs hex head self-drilling metal screws (minimum diameter 0.24 in). If the canopy is not strong enough for self-drilling screw, use 4 nuts to fix the screws from above the canopy. (picture 3)
- 3: Use a customer supplied 1-8 UNC (2A) Stem, screws into the treaded hub of the luminaire. The feed leads should through the stem. (picture 4)
- 4: Attach the junction box with another end of the stem, make the connections inside the junction box. (picture 4)
- 5: Apply sealant around stem, hub and screw holes for a complete seal.