



Item#: **55658 LED HORIZON HIGH BAY™ - 6 LAMP** LED READY FIXTURE

FEATURES

- Use 30% less energy than a traditional fluorescent fixture
- Die formed, and rigidly fabricated
- Sufficient knockouts are provided on ends and back to accommodate multiple mounting configurations
- · LED ready with non-shunted sockets
- Pre-wired at both ends
- Works with both Single-End and Double-End Direct Wire lamps
- Designed for chain mounting or adjustable cable

APPLICATION

Ideal for larger warehouses, retail applications, commercial buildings and work areas.

ELECTRICAL

Lamp Type (not included)	T5
Number of Lamps	6
Voltage	120-277V
ENVIRONMENT	
Operating Temperature	-4° ~ 122°F
Suitable Location	DAMP
Ingress Protection Rating	IP40
LIFESPAN	
Warranty (Years)	2

CONSTRUCTION

Housing	22 Gauge C.R.S		
Reflector	86% MIRO4 Aluminum		
Base / Power Supply	Hard Wired / Non-Shunted Sockets		
Finish	White		

QUALIFICATIONS



Operating temperature may vary depending on lamps used. - Specifications are subject to change without notice.

Item#: **55658** LED HORIZON HIGH BAY[™] - 6 LAMP



DIMENSIONS (Inches)

Length	48.1"
Width	16″
Height	3.5″
Weight (Lbs)	

SUPPORTING DOCUMENTS (Grey = not available at this time.)		
Product Sheet	VIEW	
Install Instructions	VIEW	

	110011	00000	00000		100110	001100	010001	° IIIII
•0								0
•0								0
°	110011	00000	011001		100110	00100	01000	°
] 3.5″	<u> </u>		0				

40.11

PACKAGING		UPC	DIMENSIONS (LxWxH)	GROSS WEIGHT (Lbs)
Master Carton	1	811768026122	48.8" x 16.3" x 3.7"	16.2
Country of Origin	China			
HS Tariff	9405.10.6020			

ORDERING

ITEM#	DESCRIPTION	CASE
55658	LED HORIZON HIGH BAY™ FOR 6 T5	1
ACCESSORIES		
54896	LOW/HIGH BAY FIXTURE OCCUPANCY PIR SENSOR 30FT DIA, 8-40FT HEIGHT 800W/1200W • 120/277V	50
54894	EXTENDER MOUNT FOR SENSOR 54896/54897/54898	100
45000	V HOOK FOR HANGING FLUORESCENT FIXTURE (2 PER SET)	1
45002	100FT ROLL NO. 12 JACK CHAIN	Per Foot

ADDITIONAL INFORMATION:

• Pairs with Direct Wire Single-End or Double-End UL Type B Lamps. Follow specific lamp installation wiring instructions for correct wiring.