



**PLEASE FIND A QUALIFIED ELECTRICIAN FOR INSTALLATION.**  
Please read the instruction before you install and use the luminaire.

90910 LED RETROFIT 4" CAN 10W/30K/MED/V4 DIMMABLE

### SPECIFICATIONS

ITEM#	WATTS	COLOR	LUMENS	CRI	VOLT	INPUT CURRENT
90910	10	3000K	700	80	120V	0.08

### HOUSING

The LIGHT comes with a dedicated LED Connector for California Title 24 Compliance, and is UL Listed for installation into Halo H7501CAT, H750RICAT, H750T and H750TCP series recessed LED housings.

### WARNING

**WARNING - Risk of fire or electric shock.** LED Retrofit Kit installation requires knowledge of luminaires electrical systems. If not qualified, do not attempt installation. Contact a qualified electrician.

**WARNING - Risk of fire or electric shock.** Install this kit only in luminaires that have the construction features and dimensions shown in the photographs and/or drawings and where the input rating of the retrofit kit does not exceed the input rating of the luminaire

Do not make or alter any open holes in an enclosure of wiring or electrical components during kit installation

**WARNING - To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects**

Supply conductors (power wires) connecting the fixture must be rated minimum 90°C. If uncertain, consult an electrician.

Risk of Electric Shock: Disconnect power or circuit breaker before installing or servicing.

**NOTE:** This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

This device may not cause harmful interference, and

This device must accept any interference received, including interference that may cause undesired operation.

**WARNING - Risk of fire or electric shock.** The electrical rating of these products are 120 Vac, the installer must determine whether they have 100-120Vac at the luminaire before installation.

Compatible with most LUTRON & LEVITON Dimmer.

**RISK OF ELECTRIC SHOCK – FOR COVERED CEILINGS ONLY. USE IN DRY AND DAMP LOCATION**

**THIS DEVICE IS NOT INTENDED FOR USE WITH EMERGENCY EXITS**

This kind of light is adjustable light, can be applied to the commonly used dimmer and dimmer range is 10% ~ 100%

### INSTALLATION



STEP 1: Shut off power before installation



STEP 2:  
Twist adaptor into socket



STEP 3:  
Insert male connector  
into female one.



STEP 4:  
Push in the can.