

# TONE-SELECT™ SLIM DOWNLIGHT

## INSTALLATION INSTRUCTIONS

**PLEASE FIND A QUALIFIED ELECTRICIAN FOR INSTALLATION.** Read the instructions before installing or use of the luminaire.

### WARNING - RISK OF FIRE OR ELECTRIC SHOCK

- To reduce the risk of electrical shock, turn off power supply before installation or servicing.
- Product must be in accordance with the NEC or applicable local electrical codes. If you are not familiar with these codes and requirements, consult a qualified electrician.
- Installation of this product requires a person familiar with the construction and operation of the luminaire's electrical system and the hazard involved. If not qualified, do not attempt installation. Contact a qualified electrician.
- Risk of fire or electric shock. Install this downlight only as shown in the photographs and/or drawings.
- To prevent wiring damage or abrasion do not expose wiring to edges of sheet metal or other sharp objects.
- The recessed downlight is intended for mounting in a covered ceiling only, where only the illuminated LED side would be exposed to dry, damp or wet locations.

## INSTALLATION



**WARNING DISCONNECT POWER BEFORE INSTALLING OR SERVICING.**

### COMMERCIAL DOWNLIGHT HOUSING COMPATIBILITY

Item #	Required Ceiling Opening
93092	6.7"

### GENERAL WIRING DIAGRAM



1. Make sure the power is turned off before installing.
2. If a new hole is needed, cut opening in the ceiling (Fig. 1), refer to table above for opening diameter.
3. Connect remote driver to the power source, see General Wiring Diagram. Close the cover of the junction box.
4. Select color temperature using slider on the side of the remote driver. Make sure the switch is not in between selections. (Fig. 2)
5. Squeeze the spring clips so they are in an upright position and insert downlight into opening. (Fig. 3)
6. Once the downlight is inside the housing, release the spring clips and continue to pushing the downlight up until it is secure and flush with ceiling. (Fig. 4)
7. Restore power, installation is complete.
8. Once the fixture is mounted in the ceiling, caulk the space between the ceiling and the shell, if necessary.

