



PREMIUM QUALITY LIGHTING

LED MODULES & DRIVER

DIMMABLE RETROFIT KIT 31W/46W/62W

INSTALL INSTRUCTIONS



PLEASE FIND A QUALIFIED ELECTRICIAN FOR INSTALLATION.
Please read the instruction before you install and use the luminaire.

SPECIFICATIONS

WATTS	COLOR	LUMENS	CRI	VOLT	INPUT VOLTAGE	DIMMABLE DRIVER
31W	35K/41K/50K	3700	80	120 / 277V	0.75A	Meanwell LPF-40D-54
46W	35K/41K/50K	5500	80	120 / 277V	0.58A	Meanwell LPF-60D-54
62W	35K/41K/50K	7400	80	120 / 277V	0.75A	Meanwell LPF-60D-42

NOTE:

- Self-taping screws to for mounting are not included and should be provided by a qualified installer.
- Avoid bending and twisting module.

WARNING

RISK OF FIRE

Risk of Electric Shock: Disconnect power or circuit breaker before installing or servicing.

NOTE: This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

This device may not cause harmful interference, and

This device must accept interference received, including interference that may cause undesired operation.

CAUTION: To avoid possible electrical shock, be sure that power supply is turned off at fuse box or circuit breaker before installing or servicing fixture. For your safety read and understand instructions completely before beginning installation.

The products intended to be used in dry locations only.

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE LUMINAIRE'S ELECTRICAL SYSTEM AND THE HAZARDS INVOLVED.

WARNING - RISK OF FIRE OR ELECTRIC SHOCK. The electrical rating of these products are 120 Vac, the installer must determine whether they have 100-120Vac at the luminaire before installation.

WARNING - RISK OF FIRE OR ELECTRIC SHOCK. Install this kit only in the luminaires that has the construction features and dimensions show in the photographs and/or drawings.

WARNING - To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects. Do not make or alter and open holes in an enclosure of wiring or electrical components during kit installation.

THIS DEVICE IS NOT INTENDED FOR USE WITH EMERGENCY EXITS

INSTALLATION



STEP 1: Shut off power before work

STEP 2: Mount module to fixture using the existing holes.

Caution: Over tightening and inappropriates sized screws can damage module.

STEP 3: Join the wiring from the 2 modules together (Img A): Blue to Blue / Brown to Brown

STEP 4: Using quick connect (included) connect driver to modules (Img B):
Blue to Black / Red to Brown

STEP 5: Connect driver to power supply
Brown: Power
Blue: Neutral
Green/Yellow: Ground

