





Item#: 55058
LED DIAMOND HIGH BAY™ - 8 LAMP
LED READY FIXTURE

#### **FEATURES**

- Use 30% less energy than a traditional fluorescent fixture
- · Die formed, and rigidly fabricated
- · LED ready with non-shunted sockets
- · Pre-wired at one end
- Sufficient knockouts are provided on ends and back to accommodate multiple mounting configurations
- Designed for pendant or chain mounting, adjustable cable

#### **APPLICATION**

Ideal for larger warehouses, retail applications, commercial buildings and work areas.

#### **ELECTRICAL**

Lamp Type (not included)	Т8
Number of Lamps	8
Voltage	120-277V

#### **ENVIRONMENT**

Operating Temperature	-4° ~ 122°F
Suitable Location	DAMP
Ingress Protection Rating	IP40

#### **LIFESPAN**

Warranty (Years)	2	

#### **CONSTRUCTION**

Housing	22 Gauge C.R.S
Reflector	86% MIRO4 Aluminum
Base / Power Supply	Hard Wired
Finish	High Gloss Baked White Enamel

#### **QUALIFICATIONS**



Operating temperature may vary depending on lamps used. • Specifications are subject to change without notice.

## Item#: **55058 LED DIAMOND HIGH BAY™ - 8 LAMP**






<b>DIMENSIONS</b> (Inches)	
Length	48.1"
Width	22.7"
Height	7.9"

# Height 7.9" Weight (Lbs) --

### **SUPPORTING DOCUMENTS** (Grey = not available at this time.)

Product Sheet	VIEW
Install Instructions	VIEW



PACKAGING		UPC	<b>DIMENSIONS</b> (LxWxH)	GROSS WEIGHT (Lbs)
Master Carton	1	811768025286	48.5" x 23.4" x 8.3"	17.6
Country of Origin	China			
HS Tariff	9405.10.6020			

#### **ORDERING**

ITEM#	DESCRIPTION	CASE
55058	8 LED DIAMOND HIGH BAY™ FOR 8/T8 W/V-HOOKS & 41.3" CHAINS - SUPERIOR LIFE®	
ACCESSOR	ES/REPLACEMENT PARTS	
54896	360° LOW/HIGH BAY FIXTURE OCCUPANCY PIR SENSOR 30' DIA, 8-40' HEIGHT 800W/1200W • 120/277V - SUPERIOR LIFE°	50
54894	EXTENDER MOUNT FOR SENSOR 54896/54897/54898 - SUPERIOR LIFE®	100
45000	V HOOK FOR HANGING FLUORESCENT FIXTURE (2 PER KIT)	1
45002	100' ROLL NO. 12 JACK CHAIN	Per Foot

#### **ADDITIONAL INFORMATION:**

• Pairs with Superior Life® Direct Wire Single-End or Double-End UL Type B Lamps. Single-end pre-wired fixtures can also be wired double-end by the end-user if needed. Follow specific lamp installation wiring instructions for correct wiring.