

82198

EMERGENCY BACK UP

700 LUMENS

FEATURES

- Works with T5 Fixture AC ballast to provide normal light when there is a power failure.
- Operates one or two lamps in the emergency mode for a minimum of 90-minutes.
- Provides a maximum initial lumen output of 700 lumens.

PRODUCT DETAILS

ELECTRICAL

- Universal input voltage 100-277V.
- LED indicator light and test switch.
- Maintenance-free, rechargeable sealed NiCd battery.
- Minimum 90-minute emergency illumination.

HOUSING

- Durable zinc plated steel construction in white finish.
- Slim design for T5 fluorescent fixtures.

LAMP COMPATIBILITY

- Operates one lamp:
- 1 Lamp** - 700 Lumens 14-28W (2'-4') T5, 24-54W (2'-4') T5HO, 32W (4') or 40W (5') T8, 44W (4') T8HO, 36-55W 4 Pin Long CFL

CONSTRUCTION


Housing	Steel
Finish	White

PACKAGING

Master Carton	15pc / N/A
Individual Box	811768023008
Country of Origin	China
HS Tariff	9405.60.6000

DIMENSIONS

Dimensions (Inches)	18.5"(L) x 1.6"(W) x 1.6"(H)
---------------------	------------------------------



ORDERING

ITEM#	DESCRIPTION	CASE
82198	EMERGENCY BACKUP 700 LUMENS 1 LAMP/90 MIN, T5 14-54W, 32-55W 4-PIN CFL, T8 32-40W	15