



FEATURES



T8 LED tube lamp provides exceptional LED lighting with reduced energy and maintenance costs. The linear LED does not require a ballast to work and offers a built-in universal line voltage driver, making it a top-of-the-line replacement for standard fluorescent lamps.


- · Simple rewiring installation allows lamps to run off main
- Wide beam design 240° light emitting area
- Exceptional efficacy
- No flickering
- Safety coated glass

SPECIFICATIONS							
Power Consumption	18W						
Input Voltage	120-277V						
Input Current	82-200						
Power Factor	0.9						
Lumens	1915						
Luminous Efficiency	100 Lm/W						
Color Temperature	5000K						
CRI	82						
LED Quantity	120						
Beam Angle	240°						
Average Life	50,000						
Dimension (Inches)	47.2"(L) x 1"(DIA)						





DIMENSIONS



90538 LINEAR LED T8

TECHNICAL DATA SHEET

ORDERING

ITEM#	DESCRIPTION	WATT	LED	LED QTY	COLOR	LUMENS	CRI	VOLT	HOURS	CASE
90538	LED SMD 4' 18WT8/50K/CL/SAFETY COATED V4 - VITA-BRITE® DLC	18	SMD	120	5000K	1915	82	120-277V	50,000	25

Please check DLC website for the most current list of approved items • www.designlights.org Published lumens on LED products are approximate and may vary slightly.